

PlusGuard 1 Series: 15 AMPS

The PlusGuard 1-15A is a Voltage Protector rated at 15 Amps, prevents damages to electrical and electronic equipment from power fluctuation, especially over and under voltage levels of long duration. The 15 sec / 30 sec / 3 min delay reconnection provides protection against power-back surge commonly experienced after resumption of power in a power cut situation. Build-in MOV excess electricity for additional protection. The PlusGuard 1-15A will automatically guard your equipment gainst brownouts or transient spikes induced by lighting or power line failure.



- > Microprocessor Controlled Design
- > Absorbs Excess Electricity through MOVs
- > Surge Suppression 900 Joules
- > Delay Reconnection Selector 15 sec / 30 sec / 3 min
- > LED Indicators Provide Status Information
- > 350 degrees plug rotation design to avoid wall sockets blocked
- > High voltage and low voltage cut-off protection

Specifications:

MODEL	PlusGuard 1-15A
INPUT	
Max. Current	15 Amp
Nominal Voltage	110/115/120Vac
Line Low Loss	90Vac
Line Low Comeback	95Vac
Line High Loss	140Vac
Line High Comeback	137Vac
Frequency	50/60Hz auto-sensing
Spike Protection	900 Joules
Connectors	Nema5-15P plug
OUTPUT	
Nominal Voltage	110/115/120Vac
Frequency	50Hz or 60Hz
Delay Timer	15 sec / 30 sec / 3 min
Connectors	Nema5-15R socket*1pc
INDICATOR	
LED	3 LEDs
ENVIRONMENT	
Operating Temperature	0°C - 40°C (32°F - 104°F)
Humidity	0-95%, non-condensing
Acoustic Noise	< 40dB at 1M

*Product specifications are subject to change without further notice.